




CJX2-1201

CJX2-1810

CJX2-2510

CJX2-3210

CJX2-D5011

CJX2-D9511

CJX2 AC Contactor(including LC1-D contactor and LC1-F Contactor),it is suitable for using in the circuit up to the rated voltage 1000V AC 50/60 Hz,and three phase, rated voltage 380V, rated current up to 630A.to switch on and off the circuit at a distance.It is also used as unfrequent start,stop and reversal of AC motor,it is combined into the electromagnetic starter with the thermal relay,combined with the auxiliary contact block,air delayer&machine-interlocking devices,it becomes the delay contactor,mechanical interlocking contactor,star-delta starter,the contactor is produced according to the standard IEC60947-4-1,GB14048.4

Main technical parameter

Model	Rated insulation voltage(V)	Rated heat current Ith(A)	Rated working current 380V AC3(A)	Control Power (kw)						Number Of the contacts	Weight (kg)
				220V	380V	415V	440V	660V	1000V		
CJX2-0910/0901	660V	25	9	2.2	4	4	4	5.5		3P+NO/3P+NC	0.32
CJX2-1210/1201		25	12	3	5.5	5.5	5.5	7.5		3P+NO/3P+NC	0.32
CJX2-1610(1810)		32	16	4	7.5	9	9	10		3P+NO	0.35
CJX2-1601(1801)		32	16	4	7.5	9	9	10		3P+NC	0.35
CJX2-2510/2501		40	25	5.5	11	11	11	15		3P+NO/3P+NC	0.51
CJX2-3210/3201		50	32	7.5	15	15	15	18.5		3P+NO/3P+NC	0.53
CJX2-4011		60	40	11	18.5	22	22	30		3P+NO+NC	1.15
CJX2-5011		80	50	15	22	25	30	33			1.20
CJX2-6311(6511)		80	63	18.5	30	37	37	37			1.25
CJX2-8011		125	80	22	37	45	45	45			1.50
CJX2-9511		125	95	25	45	45	45	45			1.55
CJX2-115	1000V	200	115	30	55	59	59	80	65	Can be installed three auxiliary contact group, nine pairs of contact combinations	3.0
CJX2-150		200	150	40	75	80	80	100	65		3.0
CJX2-185		275	185	55	90	100	100	110	100		4.1
CJX2-225		275	225	59	110	110	110	129	100		4.2